



Fall Detection Radar

User Manual

Legal Information

About this Document

- This Document includes instructions for using and managing the Product. Pictures, charts, images and all other information hereinafter are for description and explanation only.
- The information contained in the Document is subject to change, without notice, due to firmware updates or other reasons. Please find the latest version of the Document at the Hikvision website (<https://www.hikvision.com>). Unless otherwise agreed, Hangzhou Hikvision Digital Technology Co., Ltd. or its affiliates (hereinafter referred to as "Hikvision") makes no warranties, express or implied.
- Please use the Document with the guidance and assistance of professionals trained in supporting the Product.

About this Product

- This product can only enjoy the after-sales service support in the country or region where the purchase is made.
- If the product you choose is a video product, please scan the following QR code to obtain the "Initiatives on the Use of Video Products", and read it carefully.



Acknowledgment of Intellectual Property Rights

- Hikvision owns the copyrights and/or patents related to the technology embodied in the Products described in this Document, which may include licenses obtained from third parties.
- Any part of the Document, including text, pictures, graphics, etc., belongs to Hikvision. No part of this Document may be excerpted, copied, translated, or modified in whole or in part by any means without written permission.
- **HIKVISION** and other Hikvision's trademarks and logos are the properties of Hikvision in various jurisdictions.
- Other trademarks and logos mentioned are the properties of their respective owners.

LEGAL DISCLAIMER

- TO THE MAXIMUM EXTENT PERMITTED BY APPLICABLE LAW, THIS DOCUMENT AND THE PRODUCT DESCRIBED, WITH ITS HARDWARE, SOFTWARE AND FIRMWARE, ARE PROVIDED "AS IS" AND "WITH ALL FAULTS AND ERRORS". HIKVISION MAKES NO WARRANTIES, EXPRESS OR

IMPLIED, INCLUDING WITHOUT LIMITATION, MERCHANTABILITY, SATISFACTORY QUALITY, OR FITNESS FOR A PARTICULAR PURPOSE. THE USE OF THE PRODUCT BY YOU IS AT YOUR OWN RISK. IN NO EVENT WILL HIKVISION BE LIABLE TO YOU FOR ANY SPECIAL, CONSEQUENTIAL, INCIDENTAL, OR INDIRECT DAMAGES, INCLUDING, AMONG OTHERS, DAMAGES FOR LOSS OF BUSINESS PROFITS, BUSINESS INTERRUPTION, OR LOSS OF DATA, CORRUPTION OF SYSTEMS, OR LOSS OF DOCUMENTATION, WHETHER BASED ON BREACH OF CONTRACT, TORT (INCLUDING NEGLIGENCE), PRODUCT LIABILITY, OR OTHERWISE, IN CONNECTION WITH THE USE OF THE PRODUCT, EVEN IF HIKVISION HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES OR LOSS.

- YOU ACKNOWLEDGE THAT THE NATURE OF THE INTERNET PROVIDES FOR INHERENT SECURITY RISKS, AND HIKVISION SHALL NOT TAKE ANY RESPONSIBILITIES FOR ABNORMAL OPERATION, PRIVACY LEAKAGE OR OTHER DAMAGES RESULTING FROM CYBER-ATTACK, HACKER ATTACK, VIRUS INFECTION, OR OTHER INTERNET SECURITY RISKS; HOWEVER, HIKVISION WILL PROVIDE TIMELY TECHNICAL SUPPORT IF REQUIRED.
- YOU AGREE TO USE THIS PRODUCT IN COMPLIANCE WITH ALL APPLICABLE LAWS, AND YOU ARE SOLELY RESPONSIBLE FOR ENSURING THAT YOUR USE CONFORMS TO THE APPLICABLE LAW. ESPECIALLY, YOU ARE RESPONSIBLE, FOR USING THIS PRODUCT IN A MANNER THAT DOES NOT INFRINGE ON THE RIGHTS OF THIRD PARTIES, INCLUDING WITHOUT LIMITATION, RIGHTS OF PUBLICITY, INTELLECTUAL PROPERTY RIGHTS, OR DATA PROTECTION AND OTHER PRIVACY RIGHTS. YOU SHALL NOT USE THIS PRODUCT FOR ANY PROHIBITED END-USES, INCLUDING THE DEVELOPMENT OR PRODUCTION OF WEAPONS OF MASS DESTRUCTION, THE DEVELOPMENT OR PRODUCTION OF CHEMICAL OR BIOLOGICAL WEAPONS, ANY ACTIVITIES IN THE CONTEXT RELATED TO ANY NUCLEAR EXPLOSIVE OR UNSAFE NUCLEAR FUEL-CYCLE, OR IN SUPPORT OF HUMAN RIGHTS ABUSES.
- IN THE EVENT OF ANY CONFLICTS BETWEEN THIS DOCUMENT AND THE APPLICABLE LAW, THE LATTER PREVAILS.

© Hangzhou Hikvision Digital Technology Co., Ltd. All rights reserved.

Symbol Conventions

The symbols that may be found in this document are defined as follows.

Symbol	Description
 Danger	Indicates a hazardous situation which, if not avoided, will or could result in death or serious injury.
 Caution	Indicates a potentially hazardous situation which, if not avoided, could result in equipment damage, data loss, performance degradation, or unexpected results.
 Note	Provides additional information to emphasize or supplement important points of the main text.

Contents

Chapter 1 Introduction	1
1.1 Product Introduction	1
1.2 Key Feature	1
Chapter 2 Activation and Login	2
2.1 Activation	2
2.1.1 Default Information	2
2.1.2 Activate via SADP	2
2.1.3 Activate via Web Browser	3
2.2 Login	4
Chapter 3 Radar Detection	5
3.1 Set Radar Mode	5
3.2 Set Detection Parameters	6
Chapter 4 Network Configuration	9
4.1 Set IP Address	9
4.2 Set Port	11
4.3 Set IEEE 802.1X	11
4.4 Set DDNS	12
4.5 Set SNMP	13
4.6 Set Wi-Fi	14
4.7 Set Wi-Fi AP	15
4.8 Connect to Platform	17
4.8.1 Set SDK Listening	17
4.8.2 Set ISAPI Listening	17
4.8.3 Connect to OTAP	18
4.8.4 Connect to Hik-Connect	19
Chapter 5 Event and Alarm	22

5.1 Event Alarm	22
5.2 Exception Alarm	22
Chapter 6 Safety Management	23
6.1 Manage User	23
6.2 Enable User Lock	23
6.3 Set SSH	24
6.4 Enable System Log Service	24
6.5 Set Timeout Logout	24
6.6 Set Password Validity Period	25
6.7 Set IP Address Filtering	25
6.8 Install Authorized Certificate	26
6.9 Create and Install Self-signed Certificate	26
Chapter 7 Maintenance	27
7.1 View Device Information	27
7.2 Synchronize Time	27
7.3 Set DST	28
7.4 Set Serial Port	28
7.5 Reboot	29
7.6 Restore Parameters	29
7.7 Export Parameters	29
7.8 Export Debug File	30
7.9 Export Diagnosis Information	30
7.10 Upgrade	30
7.11 Import Configuration File	31
7.12 Enable Log According to Module	31

Chapter 1 Introduction

1.1 Product Introduction

Fall detection radar (hereinafter referred to as "device") adopts FMCW, MIMO, beamforming, KNN, and other technologies. It can obtain target information, including person location, speed, posture, etc., and can provide non-contact fall detection.

1.2 Key Feature

- Supports to follow the target and output the real-time location information.
- Real-time and non-contact fall detection. No privacy disclosure.
- Supports to connect to OTAP.
- Supports data transmission via Wi-Fi.
- Small size and easy installation.
- It can be used to the indoor safety and health monitoring for the elderly people in hospitals, nursing homes, and other scenarios.

Chapter 2 Activation and Login

2.1 Activation

For the first-time access, you need to activate the device by setting an admin password. No operation is allowed before activation. The device supports multiple activation methods, such as activation via SADP software, web browser, and iVMS-4200 Client.



Refer to the user manual of iVMS-4200 Client for the activation via client software.

2.1.1 Default Information

The device default information is shown as below.

- Default IP address: 192.168.1.64
- Default user name: admin

2.1.2 Activate via SADP

SADP is a tool to detect, activate, and modify the IP address of the device over the LAN.

Before You Start

- Get the SADP software from the supplied disk or the official website (<http://www.hikvision.com/>), and install it according to the prompts.
- The device and the computer that runs the SADP tool should belong to the same network segment.

The following steps show how to activate one device and modify its IP address. For batch activation and IP address modification, refer to *User Manual of SADP* for details.

Steps

1. Run the SADP software and search the online devices.
2. Find and select your device in online device list.
3. Enter a new password (admin password) and confirm the password.



STRONG PASSWORD RECOMMENDED-We highly recommend you create a strong password of your own choosing (using a minimum of 8 characters, including upper case letters, lower case letters, numbers, and special characters) in order to increase the security of your product. And we recommend you reset your password regularly, especially in the high security system, resetting the password monthly or weekly can better protect your product.

4. Click **Activate** to start activation.




Figure 2-1 Activate via SADP

Status of the device becomes **Active** after successful activation.

5. Modify IP address of the device.
 - 1) Select the device.
 - 2) Change the device IP address to the same network segment as your computer by either modifying the IP address manually or checking **Enable DHCP** (Dynamic Host Configuration Protocol).
 - 3) Enter the admin password and click **Modify** to activate your IP address modification.

2.1.3 Activate via Web Browser

Use web browser to activate the device. For the device with the DHCP enabled by default, use SADP software or client software to activate the device.

Before You Start

Ensure the device and the computer are in the LAN with the same network segment.

Steps

1. Change the IP address of your computer to the same network segment as the device.
2. Open the web browser, and enter the default IP address of the device to enter the activation interface.
3. Create and confirm the admin password.



Caution

STRONG PASSWORD RECOMMENDED-We highly recommend you create a strong password of your own choosing (using a minimum of 8 characters, including upper case letters, lower case letters, numbers, and special characters) in order to increase the security of your product. And we recommend you reset your password regularly, especially in the high security system, resetting the password monthly or weekly can better protect your product.

4. Click **OK** to complete activation.
5. Go to the network settings interface to modify IP address of the device.

2.2 Login

You can log in to the device via web browser for further operations such as live view and local configuration.

Before You Start

Connect the device to the network directly, or via a switch or a router.

Steps

1. Open the web browser, and enter the IP address of the device to enter the login interface.
2. Enter **User Name** and **Password**.
3. Click **Login**.
4. Download and install appropriate plug-in for your web browser. Follow the installation prompts to install the plug-in.
5. Reopen the web browser after the installation of the plug-in and repeat steps 1 to 3 to login.
6. **Optional:** Click **Logout** on the upper right corner of the interface to log out of the device.

Chapter 3 Radar Detection

3.1 Set Radar Mode

Wake up the radar to detect or let it stand by, and set the indicator enabling mode.

Steps

1. Go to **Configuration** → **System** → **System Settings** → **Radar** .

Radar Mode Standby Mode Wakeup Mode

Low Power Consumption Mode

Interval (sec)

Indicator

No.	On/Off	Start Time	End Time	Operation
1	Off	13:00	14:00	
2	Off	21:00	08:00	Delete

Figure 3-1 Set Radar Mode

2. Select **Radar Mode** according to the actual needs.

Standby Mode

The radar is not detecting.

Wakeup Mode

The radar is detecting.

3. **Optional:** Check **Low Power Consumption Mode** and set **Interval** according to the actual needs.

If no human body is detected after the set **Interval**, the radar will automatically switch to **Standby Mode** and detect according to the set **Interval**.

4. Set the indicator mode.

- **Scheduled Mode:** The indicator will be turned on/off according to the set **Start Time** and **End Time**. Click **Add** to add more time schedules, or click **Delete** to delete the added schedule(s).
- **Manual Switch:** Turn on/off the indicator manually.

5. Click **Save**.

3.2 Set Detection Parameters

Set radar detection parameters according to the actual needs and installation environment.

Steps

1. Click **Falling Monitoring**.
2. View the radar information.

Radar Status

The current radar status. The radar can be normally used in normal status. If the radar is in upgrading status, do not reboot the device.

Software Version

The software version of the radar.

3. Set the radar detection parameters, and click **Save**.




Figure 3-2 Set Detection Parameters

Event Triggered Time

If the target falls but does not stand up within the set time, fall alarm will be triggered. If the target falls and stands up within the set time, fall alarm will not be triggered.

Sensitivity Threshold of Human Body Detection

To detect if there exists moving or static persons in the detection area. The higher the value is, the less sensitive the detection will be. The default value is recommended.

4. Set **Detection Area**.







Figure 3-3 Set Coordinates of Detection Area

- 1) Enter the coordinates of **Left Rear Point**, **Left Front Point**, **Right Front Point**, and **Right Rear Point** of the radar detection area. You can refer to the diagram for the detection area overview.
- 2) Click **Save**.
5. If the radar detects persons in the detection areas, the real-time dynamic track of the detected person will display as red points on the middle 3D effect picture. You can hold the left button of the mouse and drag the 3D effect picture to view from 360° visual angles. You can also view the target track on the trajectory map. Drag    to adjust the viewing scale.




Figure 3-4 Real-Time Detected Target Track

6. Click **Real-Time Data** to view the detected target details. You can click **Export Data** to export the detected target details as an excel file to the computer.
7. If fall alarm is triggered, you can click **Alarm Information** to view the details of the fall alarm.

Chapter 4 Network Configuration

4.1 Set IP Address

IP address must be properly configured before you operate the device over network. IPv4 and IPv6 are both supported. Both versions can be configured simultaneously without conflicting to each other.

Steps

1. Go to **Configuration** → **Network** → **Network Parameters** → **Network Interface** .

NIC Settings

NIC Type: 10M/100M Self-adaptive

DHCP:

IPv4 Address: [Redacted]

IPv4 Subnet Mask: [Redacted]

IPv4 Default Gateway: [Redacted]

IPv6 Mode: DHCP

IPv6 Address: [Redacted]

IPv6 Subnet Mask: [Redacted]

IPv6 Default Gateway: ::

Mac Address: [Redacted]

MTU: [Redacted]

DNS Server

Preferred DNS Server: 0.0.0.0

Figure 4-1 Set IP Address

2. Set network parameters.

NIC Type

Select a NIC (Network Interface Card) type according to your network condition.

IPv4

Two modes are available.

DHCP

The device automatically gets the IP parameters from the network if you check **DHCP**. The device IP address is changed after enabling the function. You can use SADP to get the device IP address.



The network that the device is connected to should support DHCP (Dynamic Host Configuration Protocol).

Manual

You can set the device IP parameters manually. Enter **IPv4 Address**, **IPv4 Subnet Mask**, and **IPv4 Default Gateway**.

IPv6

Three IPv6 modes are available.

Route Advertisement

The IPv6 address is generated by combining the route advertisement and the device Mac address.



Route advertisement mode requires the support from the router that the device is connected to.

DHCP

The IPv6 address is assigned by the server, router, or gateway.

Manual

Enter **IPv6 Address**, **IPv6 Subnet Mask**, and **IPv6 Default Gateway**. Consult the network administrator for required information.

MTU

It stands for maximum transmission unit. It is the size of the largest protocol data unit that can be communicated in a single network layer transaction.

The valid value range of MTU is 1280 to 1500.

DNS

It stands for domain name server. It is required if you need to visit the device with domain name. And it is also required for some applications (e.g., sending email). Set **Preferred DNS Address** properly if needed.

3. Click **Save**.

4.2 Set Port

The device port can be modified when the device cannot access the network due to port conflicts.

Steps

1. Go to **Configuration** → **Network** → **Network Parameters** → **Port** .
2. You can view and edit the port.

HTTP Port

It refers to the port through which the browser accesses the device. For example, when the **HTTP Port** is modified to 81, you need to enter ***http://192.168.1.64:81*** in the browser for login.

HTTPS Port

It refers to the port through which the browser accesses the device, but certificate verification is needed.

SDK Port

It refers to the port through which the client adds the device.

SADP Port

It refers to the port through which the SADP software searches the device.

3. Click **Save**.



Note


- After editing the port, access to the device via the new port.
 - Reboot the device to bring the new settings into effect.
-

4.3 Set IEEE 802.1X

IEEE 802.1X is a port-based network access control. It enhances the security level of the LAN/WLAN. When devices connect to the network with IEEE 802.1X standard, the authentication is needed.

Steps

1. Go to **Configuration** → **Network** → **Network Parameters** → **802.1X** .
2. Check **Enable 802.1X**.



802.1X

Enable 802.1X

Protocol Type EAP-MD5

EAPOL Version 1

User Name admin

Password

Confirm Password

Save

Figure 4-2 Set IEEE 802.1X

3. Select Protocol Type and EAPOL Version.

Protocol Type

The authentication server must be configured. Register a user name and password for 802.1X in the server in advance. Enter the user name and password for authentication.

EAPOL Version

The EAPOL version must be identical with that of the router or the switch.

4. Enter User Name and Password registered in the server.

5. Confirm the password.

6. Click Save.

4.4 Set DDNS

You can use the Dynamic DNS (DDNS) for network access. The dynamic IP address of the device can be mapped to a domain name resolution server to realize the network access via domain name.

Before You Start

- Register the domain name on the DDNS server.
- Set the LAN IP address, subnet mask, gateway, and DNS server parameters.
- Complete port mapping. The default ports are 80, 8000, and 554.

Steps

- 1. Go to Configuration → Network → Network Parameters → DDNS .**
- 2. Check Enable DDNS.**

Enable DDNS	<input checked="" type="checkbox"/>
DDNS Type	IPServer ▼
Server IP	<input type="text"/>
Device Domain	<input type="text"/>
Server Port	0
User Name	<input type="text"/>
Password	<input type="text"/>
Confirm	<input type="text"/>

Figure 4-3 Set DDNS

3. Enter the server address, domain, and other information.
4. Click **Save**.
5. **Optional:** Enter the domain name in the browser address bar to access the device.

4.5 Set SNMP

You can set the SNMP network management protocol to get the alarm event and exception messages in network transmission.

Before You Start

Download the SNMP software and manage to receive the device information via SNMP port.

Steps

1. Go to **Configuration → Network → Network Parameters → SNMP** .
2. Check **Enable SNMPv1/Enable SNMP v2c/Enable SNMPv3**.

Note

- The SNMP version you select should be the same as that of the SNMP software.
- Use different versions according to the security levels required. There exists information leakage using SNMP v1 or v2. You're recommended to use SNMP v3, which provides encryption and is safer. If you use v3, HTTPS protocol must be enabled.

3. Set the SNMP parameters.

Note

For SNMP v3, you need to set **Authentication Algorithm** and **Authentication Password**.

4. Click **Save**.

4.6 Set Wi-Fi

Set Wi-Fi parameters if you want to connect the device to the network via Wi-Fi.

Steps

1. Go to **Configuration** → **Network** → **Network Parameters** → **Wi-Fi**.
2. Select **Wi-Fi Mode** as **Wi-Fi**.

Wi-Fi

Wi-Fi Enable

Wi-Fi Mode Wi-Fi Wi-Fi Hotspot

Wi-Fi Configuration

Wi-Fi List Search

No.	SSID	Working Mode	Security Mode	Channel	Signal Str...
1	[blurred]	infrastructure	WPA2-personal	1	46
2	[blurred]	infrastructure	WPA2-personal	1	44
3	[blurred]	infrastructure	WPA2-personal	2	43
4	[blurred]	infrastructure	WPA2-personal	11	42
5	[blurred]	infrastructure	WPA2-personal	6	42

Wi-Fi

SSID

Network Mode infrastructure

Security Mode

Encryption Type

Key

Save

Figure 4-4 Set Wi-Fi

3. Click **Search** and select Wi-Fi to connect in the Wi-Fi list.
4. Select **Security Mode** and **Encryption Type** according to the actual needs.
5. Enter **Key**.

6. Click **Save**.

7. **Optional:** If you want to edit the IP address connected to the Wi-Fi to make it convenient to access to the device via the IP address of WLAN, set the IP address of WLAN.

1) Select **IP Address Type** as **Static IP**.

2) Enter **IP Address**, **Subnet Mask**, **Route Address**, etc.

3) Click **Set**.

8. **Optional:** Click **Refresh** to view the Wi-Fi connection status.

4.7 Set Wi-Fi AP

The device can be set as a hotspot to share network to other devices.

Steps

1. Go to **Configuration** → **Network** → **Network Parameters** → **Wi-Fi** .

2. Select **Wi-Fi Mode** as **Wi-Fi Hotspot**.

Wi-Fi

Wi-Fi Enable

Wi-Fi Mode Wi-Fi Wi-Fi Hotspot

Wi-Fi Configuration

Wi-Fi AP

AP Broadcast

WLAN Hotspot

SSID

Security Mode

Encryption Type

Key

IP Address

Subnet Mask

DHCP Enable

Start IP Address

End IP Address

Preferred DNS Server

Alternate DNS Server

Gateway

Figure 4-5 Set Wi-Fi AP

3. Enable **AP Broadcast** or **WLAN Hotspot**.

AP Broadcast

Once enabled, other devices are able to detect the SSID of the device.

WLAN Hotspot

Enable it to share the device's internet connection. Other devices can access to internet via joining the hotspot.

4. Set Wi-Fi hotspot parameters.

- 1) Enter **SSID** (hotspot name).
- 2) Select **Security Mode** and **Encryption Type**.
- 3) Set **Key**.

5. Check **DHCP**, and enter an IP address from the address pool that allows automatic obtaining.



IP address and TCP/IP address have to be in different network segments.

6. **Optional**: Set DNS server address if you need to visit the device with domain name.
7. Click **Save**.

4.8 Connect to Platform

4.8.1 Set SDK Listening


The SDK listening can be used to receive the uploaded information of the device arming alarm.

Before You Start

The listening service has been enabled for the SDK listening, and the network communication with the device is normal.

Steps

1. Go to **Configuration** → **Network** → **Data Connection** → **SDK Listening**.
2. Check **Enable SDK Listening**.



Enable SDK Listening

IP Address/Domain

Port


 Save

Figure 4-6 Set SDK Listening

3. Set **IP Address/Domain** and **Port** if you need to upload the alarm information.
4. Click **Save**.

4.8.2 Set ISAPI Listening


ISAPI listening and SDK listening are mutually exclusive protocols. If you enable the alarms uploading listening, the device will transmit alarms via the SDK listening. If not, the device will upload alarms via ISAPI protocol after the ISAPI parameters are set.

Before You Start

The listening service has been enabled for the ISAPI host, and the network communication with the device is normal.

Steps

1. Go to **Configuration → Network → Data Connection → ISAPI Listening** .
2. Check **Enable ISAPI Listening**.



Enable ISAPI Listening

IP/Domain

Port

Host URL


 Save

Figure 4-7 Set ISAPI Listening

3. Set **IP/Domain**, **Port**, and **Host URL**.
4. Click **Save**.

4.8.3 Connect to OTAP

The device can be accessed to the maintenance platform via OTAP protocol, in order to search and acquire device information.

Before You Start

- Ensure the device can communicate with the platform normally.
- Disable the other platform accesses conflicting with OTAP.

Steps

1. Go to **Configuration → Network → Data Connection → OTAP** .
2. Check **Enable**.

OTAP server number: 1

Enable:

Address Type: Domain

Server Domain Name: [Redacted]

Server Port: [Redacted]

Device ID: [Redacted]

Key: [Redacted]

Register Status: Offline

1-16 letters or numbers, case sensitive. You are recommended to use a combination of letters or numbers.

You need to set the network parameters including device IP address, gateway, DNS, etc. to get access to the network.

Save

Figure 4-8 Connect to OTAP

3. Set corresponding parameters.

Address Type

Select the address type of the connected platform or server.

Server IP Address/Server Domain Name

The IP address or domain name of the connected platform or server.

Server Port

The port of the connected platform or server.

Device ID

The device ID should be the same with the added one on the OTAP platform.

Key

Set a custom key to encrypt the data connection between the device and the platform or server.

4. Click **Save**.

What to do next

When the registration status is online, you can manage the device via the platform or server.

4.8.4 Connect to Hik-Connect

The device can be remotely accessed via Hik-Connect.

Before You Start

- Connect the device to the Internet.
- Set the IP address, subnet mask, gateway, and DNS server of the LAN.

Steps

1. Go to **Configuration** → **Network** → **Data Connection** → **Hik-Connect Platform** .
2. Check **Enable**.

Enable

Protocol Version 3.0

Server Domain Name Custom

Register Status Offline

Offline Reason Unknown

Binding Status Unknown

Verification Code ⓘ 8-16 letters or numbers, case sensitive. You are recommended to use a combination of letters or numbers.

ⓘ You need to set the network parameters including device IP address, gateway, DNS, etc. to get access to the network.

Figure 4-9 Connect to Hik-Connect

3. **Optional:** If you have allocated a custom server, check **Custom** and enter the custom **Server Domain Name**.
4. Enter a custom **Verification Code** used to add the device via Hik-Connect.

Caution

The verification code should be 6 letters or numbers, case sensitive. You are recommended to use a combination of letters or numbers.

5. Click **Save**.
6. Add the device to Hik-Connect.
 - 1) Get and install Hik-Connect application by the following ways.
 - Visit <https://appstore.hikvision.com> to download the application according to your mobile phone system.
 - Visit the official site of our company. Then go to **Support** → **Tools** → **Hikvision App Store** .
 - Scan the QR code below to download the application.



Figure 4-10 Hik-Connect

Note

If errors like "Unknown app" occur during the installation, solve the problem in two ways.

Fall Detection Radar User Manual

- Visit <https://appstore.hikvision.com/static/help/index.html> to refer to the troubleshooting.
- Visit <https://appstore.hikvision.com/>, and click **Installation Help** at the upper right corner of the interface to refer to the troubleshooting.

2) Start the application and register a user account to log in.

3) Add device by the serial No. on the device body and the verification code.

Note

Refer to the user manual of Hik-Connect application for details.

Chapter 5 Event and Alarm

5.1 Event Alarm

The radar supports people overstay detection and fall and failure to stand up detection, and reporting the alarms to the connected platform.

Steps

1. Go to **Configuration** → **Event** → **Event Settings** .

People Overstay Alarm 1. Set people overstay alarm parameters.
Overstay Duration(min)
 ⓘ People overstay alarm is triggered when a person stays in the room for a long time.

Fall and Failure to Stand Alarm 2. Set fall and failure to stand alarm parameters.
Report Interval(s)
 ⓘ When enabled, if a person falls and fails to get up, the radar will report a fall alarm continuously to alert the caregiver.

Figure 5-1 Event Alarm

2. Set people overstay alarm.

- 1) Enable **People Overstay Alarm**.
- 2) Set **Overstay Duration**.

When a person stays in the detection area longer than the set duration, people overstay alarm will be triggered.

3. Set fall and failure to stand alarm.

- 1) Enable **Fall and Failure to Stand Alarm**.
- 2) Set **Report Interval**.

When a person falls and fails to get up within the set **Event Triggered Time** on **Falling Monitoring** interface, the radar will report fall alarms according to the set interval to alert the caregiver.

4. Click **Save**.

5.2 Exception Alarm

Set exception alarm when the network is disconnected, the IP address is conflicted, etc.

Steps

1. Go to **Configuration** → **Event** → **Alarm Linkage** → **Exception** .
2. Select the exception type(s) according to the actual needs.
3. Click **Save**.

Chapter 6 Safety Management

6.1 Manage User

The administrator can add, modify, or delete other accounts, and grant different permissions to different user levels.

Steps

1. Go to **Configuration** → **System** → **User Management** .

2. Select **Password Level**.

The password level of the added user should conform to the selected level.

3. Add a user.

1) Click **Add**.

2) Enter **User Name** and select **Type**.

3) Enter **Admin Password**, **New Password**, and confirm the password.



Caution

To increase security of using the device on the network, please change the password of your account regularly. Changing the password every 3 months is recommended. If the device is used in high-risk environment, it is recommended that the password should be changed every month or week.

4) Assign permissions to users based on needs.

User

Users can be assigned permissions of parameters settings, log search, interrogating working status, remote upgrade or formatting, shutdown, reboot, notifying monitoring center, triggering alarm output, and serial port control.

Operator

Operators can be assigned permissions of parameters settings, log search, interrogating working status, remote upgrade or formatting, shutdown, reboot, notifying monitoring center, triggering alarm output, and serial port control.

5) Click **OK**.

4. **Optional:** You can do the following operations.

Edit the user information Click  to edit the user information.

Delete the user Click  to delete the user.

6.2 Enable User Lock

To raise the data security, you are recommended to lock the current IP address.

Steps

1. Go to **Configuration → System → Security → Security Service → Software** .
2. Check **Enable User Lock**.
3. Click **Save**.

Result

When the times you entered incorrect passwords have reached the limit, the current IP address will be locked automatically.

6.3 Set SSH

To raise network security, disable SSH service. The configuration is only used to debug the device for the professionals.

Steps

1. Go to **Configuration → System → Security → Security Service → Software** .
2. Enable or disable **SSH Service**, and set **SSH Port** if you enable the function.
3. Click **Save**.

6.4 Enable System Log Service

The security audit logs refer to the security operation logs. You can search and analyze the security log files of the device so as to find out the illegal intrusion and troubleshoot the security events. Security audit logs can be saved on device internal storage. The log will be saved every half hour after device booting. Due to limited storage space, you are recommended to save the logs on a log server.

Steps

1. Go to **Configuration → System → Security → Security Service → Log Audit Service** .
2. Enable system log service.
3. Enter **IP Address** and **Port** of the log server.
4. Click **Save**.

Result

The device will upload the security audit logs to the log server regularly.

6.5 Set Timeout Logout

You can improve network access security by setting timeout logout.

Steps

1. Go to **Configuration → System → Security → Security Service → Timeout Logout** .

2. Enable timeout logout for static page.
3. Set **Max. Timeout**.
4. Click **Save**.

Result

When the page static time exceeds the set time, the device will automatically log out.

6.6 Set Password Validity Period

You can improve network access security by setting password validity period.

Steps

1. Go to **Configuration → System → Security → Security Service → Password Validity Period** .
2. Select **Validity Type**.
 - Select **Permanent**. The password will be permanently valid.
 - Select **Daily** and set **Password Expiry Time**. It will prompt you that the password is expired according to the set password expiry time, and you need to set the new password.
3. Click **Save**.

6.7 Set IP Address Filtering

You can set the IP addresses allowable and not allowable to access the device.

Steps

1. Go to **Configuration → System → Security → Security Settings** .
2. Check **Enable IP Address Filtering**.
3. Set **Filtering Mode**.

Blocklist Mode

The added IP addresses are not allowed to access the device.

Allowlist Mode

The added IP addresses are allowed to access the device.

4. Click **Add**, enter the IP address, and click **OK**.



Note

The IP address only refers to the IPv4 address.

5. **Optional**: Edit, delete, or clear the added IP addresses.
6. Click **Save**.

6.8 Install Authorized Certificate

If the demand for external access security is high, you can create and install authorized certificate via HTTPS protocol to ensure the data transmission security.

Steps

1. Go to **Configuration → Network → Network Parameters → HTTPS** .
2. Select **Create certificate request first and continue the installation**.
3. Click **Create**.
4. Follow the prompt to enter **Country/Region, Domain/IP, Validity**, and other parameters.
5. Click **Download** to download the certificate request and submit it to the trusted authority for signature.
6. Import certificate to the device.
 - Select **Signed certificate is available, start the installation directly**. Click **Browse** and **Install** to import the certificate to the device.
 - Select **Create the certificate request first and continue the installation**. Click **Browse** and **Install** to import the certificate to the device.
7. Click **Save**.

6.9 Create and Install Self-signed Certificate

HTTPS is a network protocol that enables encrypted transmission and identity authentication, which improves the security of remote access.

Steps

1. Go to **Configuration → Network → Network Parameters → HTTPS** .
2. Select **Create Self-signed Certificate**.
3. Click **Create**.
4. Follow the prompt to enter **Country/Region, Domain/IP, Validity**, and other parameters.
5. Click **OK**.

Result

The device will install the self-signed certificate by default.

Chapter 7 Maintenance

7.1 View Device Information

Basic Information and Algorithms Library Version

Go to **Configuration** → **System** → **System Settings** → **Basic Information** to view the basic information of the device.

You can edit **Device Name** and **Device No.** The device No. is used to control the device. It is recommended to reserve the default value.

Device Status

Go to **Configuration** → **System** → **System Settings** → **Device Status** to view the device status.

7.2 Synchronize Time

Synchronize the device time when it is inconsistent with the actual time.

Steps

1. Go to **Configuration** → **System** → **System Settings** → **Time Settings** .
2. Select **Time Zone**.
3. Select **Sync Mode**.

NTP Synchronization

Select it to synchronize the device time with that of the NTP server. Set **Server IP**, **NTP Port**, and **Interval**. Click **NTP Test** to test if the connection between the device and the server is normal.

Manual Synchronization

Select it to synchronize the device time with that of the computer. Set time manually, or check **Sync. with computer time**.

SDK

If the remote host has been set for the device, select it to synchronize time via the remote host.

ONVIF

Select it to synchronize time via the third-party device.

No

Select it to disable time synchronization.

All

Select it, and you can select any mode above.

4. Click **Save**.

7.3 Set DST

If the region where the device is located adopts Daylight Saving Time (DST), you can set this function.

Steps

1. Go to **Configuration** → **System** → **System Settings** → **DST** .
2. Check **Enable DST**.
3. Set **Start Time**, **End Time**, and **DST Bias**.
4. Click **Save**.

7.4 Set Serial Port


Set RS-232 parameters if you need to debug the device via RS-232 serial port.

Before You Start

The debugging device has been connected via the RS-232 serial port.

Steps

1. Go to **Configuration** → **System** → **System Settings** → **Serial Port** .



No.	Baud Rate	Data Bit	Stop Bit	Parity	Flow Control	Work Mode
1	9600 bps	8	1	None	None	Transparent Channel

Figure 7-1 Set RS-232

2. Set **Baud Rate**, **Data Bit**, **Stop Bit**, etc.



Note

The parameters should be same with those of the connected device.

3. Select **Work Mode**.

Console

Select it when you need to debug the device via RS-232 serial port.

Transparent Channel

Select it, and the network command can be transmitted to RS-232 control command via the RS-232 serial port.

Narrow Bandwidth Transmission

Reserved.

4. Click **Save**.

7.5 Reboot

When the device needs to be rebooted, reboot it via the software instead of cutting off the power directly.

Steps

1. Go to **Configuration → System → Maintenance → Upgrade & Maintenance → Device Maintenance** .
2. Click **Reboot**.
3. Click **OK** to reboot the device.



You can also click **Reboot** on the upper right corner of the page to reboot the device.

7.6 Restore Parameters

When the device is abnormal caused by the incorrect set parameters, you can restore the parameters.

Steps

1. Go to **Configuration → System → Maintenance → Upgrade & Maintenance → Device Maintenance** .
2. Select the restoration mode.
 - Click **Restore** and click **OK**. Then the parameters except the IP parameters, user parameters, and the saved parameters will be restored to the default settings.
 - Click **Restore Factory Settings** and click **OK** to restore all the parameters to the factory settings.
3. Click **OK**.

7.7 Export Parameters

You can export the parameters of one device, and import them to another device to set the two devices with the same parameters.

Steps

1. Go to **Configuration → System → Maintenance → Upgrade & Maintenance → Data Export** .
2. Click **Export** after **Configuring Parameters**.
3. Set an encryption password, confirm the password, and click **OK**.



The password is used for importing the configuration file of the current device to other devices.

4. Select the saving path, and enter the file name.

5. Click **Save**.

7.8 Export Debug File

The technicians can export the debug file to troubleshoot and maintain the device.

Steps

1. Go to **Configuration → System → Maintenance → Upgrade & Maintenance → Data Export** .
2. Click **Export** after **Debug File**.
3. Select the saving path, and enter the file name.
4. Click **Save**.

7.9 Export Diagnosis Information

The technicians can export the diagnosis information to troubleshoot and maintain the device.

Steps

1. Go to **Configuration → System → Maintenance → Upgrade & Maintenance → Data Export** .
2. Click **Export** after **Diagnosis Information**.
3. Select the saving path, and enter the file name.
4. Click **Save**.

7.10 Upgrade

Upgrade the system when you need to update the device version.

Before You Start

Prepare the upgrade file. If the upgrade file is a compressed package, it needs to be decompressed into the .dav format.

Steps

1. Go to **Configuration → System → Maintenance → Upgrade & Maintenance → Upgrade** .
2. Click **Browse** to select the upgrade file.
3. Click **Upgrade**.
4. Click **OK** in the popup window.



Note

The upgrade process will take 1 to 10 minutes. Do not cut off the power supply.

Result

The device will reboot automatically after upgrade.

7.11 Import Configuration File

Import the configuration file of another device to the current device to set the same parameters.

Before You Start

Save the configuration file to the computer.

Steps



Caution

Importing configuration file is only available to the devices of the same model and same version.

1. Go to **Configuration → System → Maintenance → Upgrade & Maintenance → Advanced Settings → Data Import** .
2. Click **Browse** to select the configuration file.
3. Click **Import**.
4. Enter the password which is set when the configuration file is exported, and click **OK**.
5. Click **OK** on the popup window.

Result


The parameters will be imported, and the device will reboot.

7.12 Enable Log According to Module

You can enable the log according to the module for debugging.

Steps

1. Go to **Configuration → System → Maintenance → Debug → Log** .
2. Check the module(s) according to your needs.
3. Click **Save**.



See Far, Go Further